

Digital Voltage Protector

Model:CZE44-16A

User Manual



Operation Instruction:

After display finished of the company logo / name / mode No.

Press button "SET" 3 seconds, then turn into the setting state.

1. Set up high cut voltage: press button "SET", flash "H" Symbol, then press "↓" or "↑" to get your needed high voltage, system will working as new setting.
2. Set up low cut voltage: press button "SET", flash "L" Symbol, then press "↓" or "↑" to get your needed low voltage, system will working as new setting.
3. Set up delay time: press button "SET", flash "d" Symbol, then press "↓" or "↑" to get your needed delay time, Delay time adjusting range: 5-999S.
4. After all parameters setting, wait 6 seconds, product will save your adjusting numbers automatic.
5. Set up default: press button "RES" 3 seconds, system back to default setting state.