

# Charger & Maintainer Lead Battery 6V, 12V & 24V

## Model : MW CC10A



### **Description:**

7-Step INTELLiGENT Car Battery Charger with CC / CV Control  
10mA for 6V, 12V & 24V LEAD Acid Batteries of the Wet, MF, VRLA, AGM & GEL

Charger lead batteries for all types of vehicles, machinery, yachts, constant current and constant voltage (CV CA). For batteries 6V- 12V- 24V automatic voltage selection depending on the battery.

### **Specifications:**

- Input Voltage 220 ~ 240VAC 50Hz 160W
- Output Current : 10.0A Max
- Charging Voltage: 7.25V / 7.45V / 14.5V / 14.9V / 29V / 29.8V
- Charging Current: Battery 6V / 1A. Battery 12V / 1A, 5A & 10A. Battery 24V / 1A & 5A
- Protections: short circuit / overload / overvoltage.
- Charge lead batteries from 7.5Ah ~ 100Ah
- Auto Start charging (trickle charge).
- Charge Battery Type : 1) Wet, MF, VRLA, AGM and GEL  
2) 6V Lead – acid battery  
3) 12V Lead – acid battery  
4) 24V Lead – acid battery
- Efficiency: >80%

### **Operating Options:**

#### **•Option 1 (Mode "1A")**

- For 6V battery charging and maintenance with 1A
- For 12V battery for charging and maintenance 1A, 5A, 10A.
- For 24V battery charging and maintenance 1A, 5A.

#### **•Option 2 (Mode "5A")**

- For 12V battery loading 5A, 10A.
- For 24V battery charging with 5A.

#### **•Option 3 (Mode "10")**

- For 12V battery charging with 10A (without service charge).
- Select "Cold Temp": charging when the ambient temperature is below 0°C.