

Mini Portable Wireless FM Receiver

Model: CZH-R01



Description:

CZH-R01 is a professional product designed for FM receiving, which has reasonably structured appearance and reliable performance, it's very simple in operation, and the quality is very high.

Features:

- **Excellent Sound Effect**

With digital adaptive noise control function, stereo sound effect is excellent.

- **High sensitivity**

High receiving sensitivity ($>1.5\text{mV}$), at least doubled higher than common radios.

- **Adopting Customized Antenna**

High-Stability receiving sensitivity, avoid negative effects from shaking of antenna or frequency change.

- **Long Working Duration**

Adopt full-capacity 1000mA lithium battery, ensure long-time operation.

- **Reasonable Design**

Customized chassis is convenient and comfortable to carry, no matter hold in hand or hang on the belt.

Specifications:

- | | |
|---|--|
| - Power supplier: BL-5C 3.7V/1000mAh | - Audio distortion: $\leq 0.2\%$ |
| - Frequency range: 87~108 MHz | - Stereo crosstalk: $\geq 36\text{dB}$ |
| - Frequency stability: $\pm 10\text{PPM}$ | - SNR: 55dB |
| - Frequency step: 200 kHz (adjustable in factory) | - Operating duration: ≥ 20 hours |
| - Receive sensitivity: $>1.5\text{mV}$ | - Charging duration: appr. 5 hours |
| - Output impedance: 32 Ω | - Size: 82*60*22mm (ledge not included) |
| - Audio output level: Max.360mV | - Weight: 0.067kg (battery not included) |

Package Contents:

- 1x CZH-R01 Receiver
- 1x Antenna
- 1x Battery
- 1x USB charger cable
- 1x Lanyard