

3x8 HDMI Switching Splitter

Model:CHDMI-38C



Description:

High performance 3-in 8-out HDMI Splitter / Switcher with remote control. It allows you to connect up to 3 HDMI sources and 8 HDMI displays. The eight HDMI outputs are identical and each supports up to 1080p. Simply press the button to switch the TV to the right.

Features:

- Built-in EDID simulator and HDCP keyset allows each output to work independently in a HDMI display.
- 3 HDMI splits sources up to 8 outputs without signal loss.
- Compliant with HDMI 1.2, HDCP 1.1 and DVI 1.0 specifications.
- Supports a wide range of PC and HDTV resolutions from VGA to UXGA and 480p to 1080p.
- Maximum resolution bandwidth is 165 MHz.
- Provides multi-channel digital audio output, with sampling rate up to 192 kHz.
- Supports both compressed and uncompressed multi-channel audio.
- Remote control
- Full HD 1080p supported.

Specifications:

Inputs	3x HDMI [3x Uncompressed AV and Data] 1x 9pin Dsub [1x RS-232 Data]
Outputs	8x HDMI [8x Uncompressed AV and Data]
Power Supply	5VDC
Frequency Bandwidth	1.65 Gbps (single link)
Operating Temperature Range	0°C ~ 40°C
Dimensions	436mm [W] x 116mm [D] x 44mm [H]
Weight	1.6Kg

More Detailed Photos:



Made in Taiwan