



Digital Multimeter

Model: YF-3503



Features:

- Digital multimeter.
- Display 3 1/2 digits.
- Transistor gain
- TTL logic tester.
- Low battery indication.
- Battery test.
- Holster

Specifications:

- 3 1/2 digits , maximum display 2000 .
- Polarity Display: Negative input, automatically display the "one" symbol.
- Overload Display: The LCD screen displays "1".
- Low Battery Display: When the LCD screen displays "BAT", it indicates that the battery needs to be replaced.
- AC Voltage: 200mV, 2V, 20V, 200V, 750V.
- DC Voltage: 200mV, 2V, 20V, 200V, 1000V.
- DC Current: 200 μ A, 2mA, 20mA, 200mA, 20A.
- AC Current: 200 μ A, 2mA, 20mA, 200mA, 20A.
- Ohm: 200 Ω , 2K Ω , 20K Ω , 200K Ω , 2M Ω , 20M Ω .
- Capacitance: 2nF, 20nF, 200nF, 2000nF, 20 μ F
- Diode measurement / logic measurement / transistor measurement / battery measurement / conduction measurement.
- Conduction Measurement: $\leq 40 \Omega$
- Battery Measurement: 1.5V, 9V
- Size: 143*74*38mm
- Weight: 257g (with Battery).

More Detailed Photos:



Made in Taiwan