

# Current Transformer

## Model: BH-0.66CT



### Description:

- BH series current transformer is suitable of applying in electric system with rated voltage 0.66KV or below, rated frequency 50/60Hz, measurement of electric energy, current and protection of relays.
- The product comply with GB1208-97 standard.

### Features:

- AC Circuit, 100/5 Rated Current Ratio.
- The middle of the window for the bus to wear around.
- Protects equipment against circuit damage.
- Tests, controls, displays and records electrical equipment operation.

### Specifications:

Rated Current Ratio	100/5
Accuracy Class	0.5
Rated Voltage	0.66KV
Working Frequency	50Hz - 60Hz
Conductor Through	1T
Primary Current	100A 5VA
Power	5/3.75VA
Secondary Current	5A 50/60Hz 660V
Total Size	80 x 60 x 36mm
Case Material	Plastic
Color	Gray
Weight	252g
Package Content	1 x Current Transformer Installing Kits